

# FEOV/CE 90-240V AC - Valvola a farfalla a comando elettrico DN 40:100

Valvola a farfalla con attuatore elettrico multivolt 90-240 V AC 50-60 Hz.



## EPDM

| Codice     | d        | DN  | PN | B <sub>2</sub> | H   | Z  | A <sub>min</sub> | A <sub>max</sub> | f  | U | B <sub>7</sub> | T <sub>1</sub> | T <sub>2</sub> | T <sub>3</sub> | g    |
|------------|----------|-----|----|----------------|-----|----|------------------|------------------|----|---|----------------|----------------|----------------|----------------|------|
| FEOVEM050E | 50-1"1/2 | 40  | 16 | 60             | 132 | 33 | 93,5             | 109              | 19 | 4 | 253            | 92             | 187            | 91             | 2074 |
| FEOVEM063E | 63-2"    | 50  | 16 | 70             | 147 | 43 | 108              | 124              | 19 | 4 | 259            | 92             | 187            | 91             | 2254 |
| FEOVEM075E | 75-2"1/2 | 65  | 10 | 80             | 165 | 46 | 128              | 144              | 19 | 4 | 266            | 92             | 187            | 91             | 2480 |
| FEOVEM090E | 90-3"    | 80  | 10 | 90             | 130 | 49 | 145              | 159              | 19 | 4 | 308            | 128            | 202            | 95,5           | 4000 |
| FEOVEM110E | 110-4"   | 100 | 10 | 105            | 150 | 56 | 165              | 190              | 19 | 4 | 322            | 128            | 202            | 95,5           | 4350 |

## FKM

| Codice     | d        | DN  | PN | B <sub>2</sub> | H   | Z  | A <sub>min</sub> | A <sub>max</sub> | f  | U | B <sub>7</sub> | T <sub>1</sub> | T <sub>2</sub> | T <sub>3</sub> | g    |
|------------|----------|-----|----|----------------|-----|----|------------------|------------------|----|---|----------------|----------------|----------------|----------------|------|
| FEOVEM050F | 50-1"1/2 | 40  | 16 | 60             | 132 | 33 | 93,5             | 109              | 19 | 4 | 253            | 92             | 187            | 91             | 2074 |
| FEOVEM063F | 63-2"    | 50  | 16 | 70             | 147 | 43 | 108              | 124              | 19 | 4 | 259            | 92             | 187            | 91             | 2254 |
| FEOVEM075F | 75-2"1/2 | 65  | 10 | 80             | 165 | 46 | 128              | 144              | 19 | 4 | 266            | 92             | 187            | 91             | 2480 |
| FEOVEM090F | 90-3"    | 80  | 10 | 90             | 130 | 49 | 145              | 159              | 19 | 4 | 308            | 128            | 202            | 95,5           | 4000 |
| FEOVEM110F | 110-4"   | 100 | 10 | 105            | 150 | 56 | 165              | 190              | 19 | 4 | 322            | 128            | 202            | 95,5           | 4350 |